

9. CALIBRATION


9.1 COMPASS CALIBRATION

The compass is very sensitive to electromagnetic interference which can cause abnormal compass data and lead to poor flight performance or even flight failure. Regular calibration enables the compass is in optimum performance.

- ⊘ Do not calibrate the compass in a strong magnetic field
- Do not carry ferromagnetic materials with you while calibrating the compass, such as keys, cell phones, etc.

MANUAL COMPASS CALIBRATION PROCEDURES

- 1) Push the left stick to the most left side, and move the right stick left to right quickly until the transmitter displays "Calibrate Compass 1"
- 2) Rotate the X4 horizontally clock-wise until the LCD screen displays " Calibrate Compass 2"
- 3) Put the X4 nose down and rotate it vertically clock-wise until the " Calibrate Compass 2" on screen disappears.
- 4) Calibration done.




9.2 HORIZONTAL CALIBRATION

Horizontal calibration is required when the X4 drifts during flight.

Please follow the calibrating procedures:

- 1) Push the left stick to the most right side, and move the right stick left to right quickly until the 4 LED indicators blink in yellow slowly.
- 2) Calibration succeeded when the 4 LED indicators stop blinking slowly.




9.3 ROTATION CALIBRATION

Rotation calibration is required when the X4 yaws during flight.

Please follow the calibrating procedures and be sure that the X4 always on horizontal surface:


- 1) Push the left stick to the top side, and move the right stick up and down quickly until the 4 LED indicators blink in yellow slowly
- 2) When the 4 LED indicators turns into red and blink circularly, rotate the X4 horizontally clock-wise until the 4 LED indicators remain lighted in green
- 3) When the 4 LED indicators turns into red again, rotate the X4 horizontally clock-wise until the 4 LED indicators explosion-flashing simultaneously
- 4) Calibration done



10. TRANSMITTER STICK CALIBRATION

Mode 2: Push both sticks to the upper left corner and power on the transmitter simultaneously, the LCD will display "Calibrate Stick Mode 2", rotate both sticks in circles for three times, release both sticks, then press any trim for 1.5 seconds until one "beep" heard which indicates a successful calibration.

Mode 1: Push the left stick to the upper left corner and the right stick to the upper right corner and power on the transmitter simultaneously, the LCD will display "Calibrate Stick Mode 1", rotate both sticks in circles for three times, release both sticks, then press any trim for 1.5 seconds until one "beep" heard which indicates a successful calibration.




 The transmitter mode can be shifted according to the above operation.


11. FREQUENCY SELECTABLE 5.8GHZ

The transmitter will automatically find the best frequency to ensure a live video with good quality of transmission. Please re-select the frequency to get a better video transmission when necessary.

Pull the throttle stick to the lowest position and press the Elevator stick for 1.5 second to enter into the MAIN MENU interface. Push the Elevator stick up/down to select "5.8G Frequency", push the stick to the right to enter into the "5.8G frequency" interface, select a matched frequency.



EXPLODED VIEW



NO.	PART NAME	QTY
01	Lower Body Shell	1
02	Main Control Board	1
03	Power Board	1
04	5.8 GHz Transmission PCBA	1
05	Compass PCBA	1
06	GPS Module	1
07	USB PCBA	1
08	Camera Module	1
09	ESC	4
10	Motor A	2
11	Motor B	2
12	Li-Po Battery	1
13	2.4G Antenna	1
14	5.8G Antenna	1
15	LED PCBA	4
16	Upper Body Shell	1
17	2.4GHz Shielding Case	1
18	Sponge	1

NO.	PART NAME	QTY
19	Battery Cover	1
20	Canopy	1
21	Eye Lampshade	1
22	Motor A Lampshade	2
23	Motor B Lampshade	2
24	Lens Holder	1
25	Propeller A	2
26	Propeller B	2
27	Rubber Feet	4
28	Shielding Case	1
29	Sponge	1
30	Screw	4
31	Screw	10
32	Screw	16
33	Screw	8
34	Screw	2
35	Screw	16

H501S PRO SPARE PART CHART



H501S-01
Body Shell
Set- White



H501S-22
Body Shell
Set- Black




H501S-02B
Battery
Cover- Black



H501S-02
Battery
Cover- White



H501S-03
Canopy



H109-04
Rubber Feet



H501S-04
Screw Set




H501S-05
Propeller
A- Gold



H501S-06
Propeller
B- Gold



H501S-05B
Propeller
A- Black



H501S-06B
Propeller
B- Black




H501S-07
Brushless
Motor A



H501S-08
Brushless
Motor B




H501S-09
PCB Module



H501S-10
Flight Control
PCB Module



H501S-11
5.8G Transmission
Module



H501S-12
GPS Module



H501S-13
Compass Module



H501S-14
Lipo Battery
2700MAh



H501S-27
Remote



H301S-11
Adapter



H301S-12
Balance Charger



H501S-16
U Wrench



H501S-17
Eye Lampshade



H501S-18
Motor LED
Lampshade



H501S-19
ESC



H501S-20
LED PCBAs



H501S-21
2.4G Receiver
Module

FCC INFORMATION

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the local dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

ENVIRONMENTALLY FRIENDLY DISPOSAL

Old electrical appliances must not be disposed of together with the residual waste, but have to be disposed of separately. The disposal at the communal collecting point via private persons is for free.

The owner of old appliances is responsible to bring the appliances to these collecting points or to similar collection points. With this little personal effort, you contribute to recycle valuable raw materials and the treatment of toxic substances.



Electrical and electronic equipment that are supplied with batteries (including internal batteries)

WEEE Directive & Product Disposal

At the end of its serviceable life, this product should not be treated as household or general waste. It should be handed over to the applicable collection point for the recycling of electrical and electronic equipment, or returned to the supplier for disposal.

Internal / Supplied Batteries.

This symbol on the battery indicates that the battery is to be collected separately.

This battery is designed for separate collection at an appropriate collection point.



User manual is subject to change without prior notice due to unforeseen product upgrades.

Download the latest user manual from

WWW.HUBSAN.COM

VERSION 1.1 EN

